



Chain Hoist Electrical Pinout Chart




Dual Twist

L16-20 Pinout

Power

X = L1 Z = L3
Y = L2 G = GROUND




L16-20P

L14-20 Pinout

Control

(Motion Labs and Skjonberg standard)

X = COMMON Y = DOWN W = UP




L14-20R

P14 Pinout

Power & Control


A = L1 E = COMMON
B = L2 F = DOWN
C = L3 N = GROUND
D = UP



P14 Plug

C7 Pinout Chart

NUMBER	L1	L2	L3	GROUND	COMMON	UP	DOWN
C7-30	1	2	3	4	6	5	7
C7-31	3	2	1	5	7	4	6
C7-32	1	3	7	5	4	6	2
C7-33	1	2	7	5	3	4	6
C7-34	1	2	3	5	7	4	6
C7-35	1	2	3	5	7	6	4
C7-36	2	1	3	4	6	5	7
C7-37	2	1	3	4	6	7	5
C7-38	1	2	3	5	6	4	7



C7 Plug

Data valid as of January 13, 2025



www.a4direct.us
info@a4direct.us
1-800-411-0065



www.tomcatglobal.com
sales@tomcatusa.com
1-800-298-7877

